



# Canon RC-IP100 remote camera controller

Pan, tilt and zoom effortlessly with this high-quality controller featuring a multi-function joystick and intuitive touchscreen for easy control of up to 100 cameras over IP.

## Control up to 100 cameras remotely

A multi camera set-up over IP is easy with the RC-IP100 and offers control of up to 100 PTZ units with just one operator and LAN cable, making remote production beautifully streamlined.

## Pinpoint zooming for the perfect shot

A professional zoom rocker enables smooth and precise wide-to-tele adjustments and lets you zoom with the same high degree of control as seen on pro camcorders.

## Flexible connectivity

Equipped with Serial and LAN integration, control over IP based PTZ cameras is made easier and more intuitive, giving you greater freedom in controlling your setup.

# Specifications

## 7-inch touchscreen

For easy switching between up to 100 cameras and settings

## Customisable controls

User assignable buttons and customisable control knob

## Manage and adjust with fingertip simplicity

An intuitive 7-inch (17.78 cm) touch screen allows easy switching between cameras as well as quick management of focus settings, white balance, shutter speeds and much more.

## Assign and refine with custom controls

With two user assignable buttons as well as two dedicated function buttons and customisable control knob on the joystick the user can optimise their setup for a wide range of shooting scenarios.

## Multi-function joystick

Precisely adjust camera movements

## Flexible connectivity

Serial and LAN integration

## Perfect precision with a multifunction joystick

A multi-function joystick allows precise adjustment over camera movements and settings while a control grip on top of the stick allows zoom, focus and iris control.

## Manage up to 100 stored positions

Appoint up to 100 pre-set angles per camera using the 7" touchscreen, and utilise the trace function to allow recording of up to ten different movements (pan, tilt, zoom) which can be reproduced at the touch of a button.

## Professional zoom rocker

For smooth and precise wide-to-tele adjustments



[2] Cable Clamp Hole

[4] LAN Terminal

[6] Tally Terminal

[8] Serial Terminal



[1] Power Switch

[3] DC Input Terminal

[5] Service Terminal

[7] SETTING Switch

# What's in the box

RC-IP100 Main Unit

---

Wire Clamp

---

Screw

---

AC Adapter

---

AC Cable

# ➤ Specifications in detail

## General

Power	12V DC (AC adapter power supply) CAUTION: Utilize included 12V DC power supply only. All other power supplies may cause permanent damage to controller.
Dimensions	Width 350mm (13.7 in) x Height 110mm (4.3 in) x Depth 182 mm (7.1 in)
Weight	Approx. 2.1 kg (4.6 lbs.)
Operating Temperature	0 °C ~ 40 °C

## Camera Control

Controller Supported Cameras	CR-N500, CR-N300, CR-X300, CR-X500
Number of Connectable Cameras	1 unit (RS422) 100 units (*When RS422 is connected: 99 units)
Preset (Store/Play/Delete)	100 per camera
Trace (Store/Play/Delete)	10 per camera
Communication System	IPv4
Touch Panel	7-inch (diagonal) touch screen

## Terminal

Tally	D-Sub 9 pin
LAN	R-45 x 1 (10 BASE-T/100 BASE-TX)
Serial	RJ-45 x 1 (RS422)

## DISCLAIMERS

Warning  
This is a class A product. In a domestic environment this product may cause radio interference in which case the user may be required to take adequate measures.